


E-TOUCH ICLOUD SETUP

1: Standard Package Support: H/HD/HE Series

2: E-touch / iCloud for Mobile phone software: vMyEyeCloud / Android, vMyEyeCloud / iPhone

- 1、Pls turn on the DVR
- 2、Make sure that DVR have already connected the Internet
- 3、Pls link to <http://xmeye.net> on your PC, that should be as below:



- 4、Pls Download Web Active and run the Active

- a. Install the Active as below:




- b. Press "Next", and get into the next step as below:



c. Press "Next" as below:



d. Choose the storage directory, press "Next" as below:



e. Press "Next" and finish install as below:



5. After finish install, pls get back to: <http://xmeye.net>.

1) Register

a. press Register as below:

Username	<input type="text"/>
True Name	<input type="text"/>
Sex	Male ▼
Contact	<input type="text"/>
Address	<input type="text"/>
E-mail	<input type="text"/> (You can get your password back by the E-Mail)
Password	<input type="password"/>
Confirm	<input type="password"/>
<div>Ok Cancel</div>	

b. Pls log in as below:

My Devices Device Manage User Info Logout

Add				
MAC Address	Device Name	Username	Password	Operation

User Info Edit	
Username	kenny lai
True Name	kenny lai
The last login time	2012-08-29 10:55:45

c. Device Manage and add as below:

Must be same with DVR

MAC Address (MAC contain 12 charactors with hex)

Device Name

Must be same with DVR

Username (default is "admin")

Must be same with DVR

Password (default is null)

Ok Cancel

Pls check the Serial number as below: DVR's main menu —INFO—VERSION-----Serial NO

Version

Record Channel	4
Extra Channel	0
Alarm In	4
Alarm Output	0
System	V4.00.R10.04752062.1
Build Date	2012-10-24 17:02:04
MAC	001000017633
SerialNo	fabffa9d1763ebc
Status	5
Nat status	Connected
Nat status code	2:220.231.192.70

OK

d. After setting, press "My Devices" as below:

